

## 4K HDMI® to 12G-SDI Converter + Frame Synchronizer

- Supports 12G / 6G / 3G / 1.5G / SD-SDI Signals
- 3G-SDI Level A And Level B Support
- Integrated Frame Synchronizer
- Multi-Format Sync Reference Input - Cross Lock Compatible
- 2 x SDI Outputs With Optional SDI Fiber Output
- HDMI Embedded PCM Audio Passes Transparently
- Balanced Analog Audio, Unbalanced Line Level Audio, Or AES Input
- Selectable AES Channel For Embedding External Audio
- HDMI, Reference And Audio Present LED Indication
- LynxCentraal & yelloGUI Compatible For Additional Internal Settings



Shown with Fiber SFP Option Installed

The CHD 1412 is a versatile and compact HDMI to SDI converter with integrated frame synchronizer. It is an ideal solution for any application which requires a fully synchronized SDI input from an external asynchronous HDMI source.

The flexible reference sync input will accept any analog video sync format including SD bi-level sync, black burst, colorbars and tri-level sync. The sync input is auto detecting and fully cross lock compatible. For example: An SDTV reference can be used to frequency lock an HD HDMI input. If no reference is present, the converter performs a standard asynchronous HDMI to SDI conversion. It can also lock to the HDMI input. A pair of stereo analog inputs can be embedded into any AES channel. Audio inputs can be either professional balanced audio with selectable full scale level, or unbalanced consumer line level audio. By default any PCM audio present in the HDMI stream will be embedded into the SDI output [encoded audio such as AC3 / DD+ etc. is not supported] or it can be replaced with the external audio signals.

The module is also compatible with LynxCentraal and yelloGUI software packages, which provide access to a host of additional internal settings including adjustable video delay for timing purposes.

An SDI fiber output is also provided with a variety of plug in SFP options available.



**Note:** For legal reasons, HDMI capture devices from LYNX Technik AG are designed not to capture, convert or transmit video or audio from HDCP copy-protected sources (e.g. Satellite receivers, Cable receivers, BD players etc.)

### Fiber I/O Options:

SDI Fiber Transmitter Options		
Model	Description	Power
OH-TX-12G-LC	SFP Fiber TX - Singlemode - LC connector - 10km*	-5 ... +0.5dBm
OH-TX-4-12G-LC	SFP Fiber TX - Singlemode - LC, ST or SC conn. - 40km*	-0.5 ... +3dBm
OH-TX-12G-XXXX-LC	CWDM SFP Fiber TX - Singlemode LC Conn. - 10km* XXXX=Wavelength, 18 according to ITUT G692.2 1270 -1610nm	-2 ... +3dBm
OH-TX-1 LC/ST/SC	3G SFP Fiber TX - Singlemode - LC/ST/SC connector - 10km*	-8 ... -3dBm
OH-TX-4-XXXX-LC	3G CWDM SFP Fiber TX - Singlemode - LC connector - 40km*	-4 ... +2dBm
OH-TX-8-XXXX-LC	3G CWDM SFP Fiber TX - Singlemode - LC connector - 80km*	+1 ... +5dBm

\* Distance is an approximation. Actual distances achieved can be longer or shorter depending on the type of fiber cable and accumulated optical losses in the fiber link. Determine link losses and perform optical budget calculations to ensure correct operation.

More SFP options are available.

### Technical Specifications

<b>HDMI Input</b>	Type A 2.0b connector for up to 2160p60  Up to 8 channels embedded audio in HDMI is passed transparently or replaced with external analog audio input
<b>Reference Input</b>	SDTV: Analog 525 or 625 bi-level sync, black burst or colorbars HDTV, 3G, 12G: All tri-level sync standards (exceptions 1080p 50/59.94/60Hz) Cross lock compatible  SMPTe 274M, SMPTe 296M - 75 Ohm BNC connector
<b>Frame Synchronizer</b>	Functional if valid reference is detected, otherwise operates in free run (async) mode. External audio and HDMI input are frequency locked to external reference, fully cross lock compatible across standards. One frame adjustable delay (in line and pixel increments) using LynxCentraal or yelloGUI
<b>SDI Outputs</b>	2 x SDI video, 75 Ohm BNC (both have the same signal - NOT dual link)  SMPTe 259M, SMPTe 292M, SMPTe 424M, SMPTe 2081-1, SMPTe 2082-1  Electrical Return Loss:    to 1.5GHz    to 3GHz    to 6GHz    to 12GHz >15dB       >10dB       >7dB       >4dB
<b>Fiber Output</b>	Optional plug in SFP for optical SDI output (see fiber options table) SMPTe 297 - 2006
<b>Audio Inputs</b>	Left and right analog audio using 3.5mm jack plugs  10k Ohm differential balanced input mode with 24,22,20,18,15,12 dBu and User definable full scale level (selectable)  Unbalanced mode with (line level) at -10 dBV (3.5mm Jack Plug to RCA connection adapters supplied)  Selectable AES channel for audio embedding (1 through 8) (Overwrites any HDMI embedded audio present in selected channel)  Frequency response: <+/- 0.1dB 20Hz to 20KHz  48kHz A/D sample rate (frequency locked to SDI output)
<b>Power</b>	+12V DC @ 10.0W (excl. SFP) nominal - ( supports 10 - 14V DC input range )
<b>Physical</b>	Size (incl. connectors): 140mm x 90mm x 22mm (5.51" x 3.54" x 0.86") Weight (excl. SFP): 207g (7.3oz)
<b>Ambient</b>	5 - 40°C (41 - 104°F) 90% Humidity (non condensing)
<b>Model #</b>	CHD 1412 - ( EAN# 4250479328112 )
<b>Includes</b>	Module, AC power supply, RCA adapters, HDMI + USB cable



## Video Output Resolution

The module does not have an internal scaler and no de-interlacer. If the input resolution does not match any of the supported SDI formats, the module by default will select an appropriate SDI standard with a similar number of line pixels and map the signal into the SDI output. This may result in some image cropping (cut) or boxing (blanking) of the overshot area. To change the output format, please connect the module to a PC or Mac via either yelloGUI or LynxCentral.

HDMI Input	SDI Output				
	SDTV	720p	1080i	1080p	2160p
SDTV [720x 525/625]	N	B	B	B	B
720p [1280x720]	C	N	B	B	B
1080i [1920x1080]	C	C	N	N	B
1080p [1920x1080]	C	C	N	N	B
2160p [3840x2160]	C	C	C	C	N

HDMI Input	SDI Output				
	SDTV	720p	1080i	1080p	2160p
VGA [640x480]	B	B	B	B	B
SVGA [800x600]	C	B	B	B	B
XGA [1024x768]	C	CV/BH	B	B	B
WXGA [1280x768]	C	CV	B	B	B
WUXGA [1920x1200]	C	C	CV	CV	B
WQXGA [2560x1600]	C	C	C	C	B
WQXGA [3840x2400]	C	C	C	C	CV

Legend		CV/BH	Crop: Vertical / Boxing: Horizontal
C	Cropping (Horizontal and Vertical)	CV	Crop: Vertical
B	Boxing (Horizontal and Vertical)	N	Output = Input

## Cross Lock and Frame Rate Conversion

The frame synchronizer is fully cross lock compatible, meaning it can cross lock between different standards. With a given reference signal connected, the synchronizer will drop or repeat frames to achieve a correctly synchronized ( frame rate converted ) SDI output.

Reference Signal (fps)	SDI Output	Input Video Standard												
		525 i / 59	625 i / 50	1080 i / 50	1080 i / 59	1080 i / 60	16:9 p / 23	16:9 p / 24	16:9 p / 25	16:9 p / 29	16:9 p / 30	16:9 p / 50	16:9 p / 59	16:9 p / 60
23	SDI Output	525 i / 59	525 i / 59	1080 i / 59	1080 i / 59	1080 i / 59	16:9 p / 23	16:9 p / 23	16:9 p / 23	16:9 p / 23	16:9 p / 23	16:9 p / 59	16:9 p / 59	16:9 p / 59
24		625 i / 50	625 i / 50	1080 i / 50	1080 i / 50	1080 i / 50	16:9 p / 24	16:9 p / 24	16:9 p / 24	16:9 p / 24	16:9 p / 24	16:9 p / 50	16:9 p / 50	16:9 p / 50
25/50		625 i / 50	625 i / 50	1080 i / 50	1080 i / 50	1080 i / 50	16:9 p / 25	16:9 p / 25	16:9 p / 25	16:9 p / 25	16:9 p / 25	16:9 p / 50	16:9 p / 50	16:9 p / 50
29/59		525 i / 59	525 i / 59	1080 i / 59	1080 i / 59	1080 i / 59	16:9 p / 29	16:9 p / 29	16:9 p / 29	16:9 p / 29	16:9 p / 29	16:9 p / 59	16:9 p / 59	16:9 p / 59
30/60		625 i / 50	625 i / 50	1080 i / 60	1080 i / 60	1080 i / 60	16:9 p / 30	16:9 p / 30	16:9 p / 30	16:9 p / 30	16:9 p / 30	16:9 p / 60	16:9 p / 60	16:9 p / 60

DROP FRAME CONVERSION

REPEAT FRAME CONVERSION

## CHD 1412 Frame Rate Conversion Applications

In North American (or legacy NTSC) markets the HDMI signals from most devices tends to be at the consumer 60Hz frame rate and not 59.94Hz which is the required frame rate for broadcast and production.

The CHD 1412 can be used to solve this problem and convert a 60Hz HDMI signal to a 59.94Hz SDI signal. This is accomplished using the integrated frame synchronizer (which will drop frames to achieve the correct frame rate)

If fact, the module can also convert between 50Hz and 60Hz standards using the frame synchronizer, which is useful for monitoring applications.

Its also possible to precisely adjust the timing of the SDI output up to one full frame relative to the reference sync in pixel and line increments - which is useful for timing and synchronizing SDI sources into production switchers or routers etc.

